



Welcome to.....



More Information About **R-Core Transformer**

Detailed Product Description



R-Core Transformer Features:

- *Without fracture;
- *With round section area;
- *Horizontal, thinness, adapt to high density' installation;

Compare to E&I transformer:

- a. 30% smaller and 40% lighter;
- b. Low magnetic loss upward of 90%;
- c. Temperature raise lower under 50%;
- d. Winding is round, medial winding length reduce 6% ~10%, low cuprum loss.

Product Directory

Power Transformer

Audio Transformer

Three Phase Transformer

Auto Transformer

Control Transformer

Power Adapter

Special Transformer

Sizes Of Form And Installation:

Model	Capacity (VA)	Size Of Product(mm)			Installation Size(mm)				Weight kg
		A	W	X	E	F	G	T	
PR-10	15	74	61	37	68.4	48	4×5	1.0	0.4
PR-20	25	81	70	39	55	50	M3	1.0	0.5
PR-30	40	96	77	42	70	60	Φ5	1.0	0.7
PR-40	50	98	80	44	70	60	Φ5	1.0	0.9
PR-50	60	101	92	48	75	65	Φ5	1.0	1.0
PR-80	100	124	90	52	90	70	Φ5	1.2	1.4
PR-100	120	124	103	55	100	80	Φ5	1.2	1.7
PR-160	180	138	115	63	100	85	Φ5	1.6	2.6
PR-260	280	156	121	66	130	95	Φ5	1.6	3.1
PR-320	380	163	128	70	135	95	Φ5	1.6	3.8
PR-600	600	182	145	85	142	100	Φ8	1.6	6.5
PR-1000	1000	222	172	99	180	140	Φ8	2.6	10.5

The Picture About R-Core Transformer's Size And Installaion

